

# LED Exterior Bulb

## Model No:LLS-B

### Post Top, Yard and Barn Lights



Model selection is LLS-B-Bulb Watts.

Example: To replace a 250w MH, the model would be LLS-B-36

LLS Model # & Information	Bulb Watts	Length & Dia. (inches)	Suggested MH/HPS Replacement
B-20	20	6. 9/3. 4	100w
B-24	24	9. 6/4. 3	150w
B-30	30	10. 4/4. 3	200w
B-36	36	10. 4/4. 3	250w
<b>Input Volatage</b>	85 -240V or 277V		
<b>Power Factor</b>	>. 99		
<b>Base</b>	E27, E39		
<b>Luminous flux</b>	110 lm/w		
<b>Degrees</b>	360°		
<b>CRI</b>	>80		
<b>Life Span</b>	>80, 000hrs		
<b>Net Weight</b>	1. 5 kg		
<b>Certificate:</b>	CE, RoHS, UL		
<b>Color Temperature</b>	3000 – 7000k		
<b>Working Tempreture</b>	-35° C – 45° C		
<b>IP Rating</b>	Ip65		
<b>Warranty</b>	5 Years		

Saves a bundle on energy and maintenance; No more expensive yearly change outs!



**Replaces 75 to 250w  
MH/HPS**